

**AMENDMENTS TO THE CLAIMS**

1. (Previously Presented) An interface circuit for processing an analog color signal comprising:
  - a phase locked loop (PLL) circuit adapted to generate a plurality of phased signals from a synchronizing signal that is associated with the analog color signal;
  - a phase adjuster adapted to generate an adjustable delay signal from two of the plurality of phased signals that are apart from each other by an odd multiple of approximately 45 degrees; and
  - an analog to digital converter adapted to improve processing of the analog color signal by choosing an adjustment to the delay signal, wherein at least one simulated phase signal is provided.
2. (Original) The circuit of claim 1, wherein the synchronizing signal is intended to generate a pixel clock in a display, and the phased signals replicate those of the pixel clock.
3. (Previously Presented) The circuit of claim 1, wherein the phase adjuster includes:
  - a first phase selector for selecting a first one of the phased signals;
  - a second phase selector for selecting a second one of the phased signals; and
  - a phase mixer for multiplying the first selected phased signal with a first weight, multiplying the second selected phased signal with a second weight, and adding together the first and the second multiplied phased signals to derive the adjustable delay signal.
4. (Original) The circuit of claim 3, wherein the phase adjuster further includes:
  - a decoder to generate phase selection signals for selecting the first and second phased signals.
5. (Currently Amended) The circuit of claim 4, wherein the first selected phased signal, the second selected phased signal, and at least one some of the selected phase information selection signal[[s]] are received into the phase mixer.

6. (Previously Presented) The circuit of claim 3, wherein  
the phase adjuster further includes:  
a Phase Digital to Analog Converter for generating a first weight signal representing the first weight and a second weight signal representing the second weight, and  
wherein the phase mixer receives the first weight signal and the second weight signal to derive the adjustable delay signal.
7. (Original) The circuit of claim 6, wherein  
the phase adjuster further includes:  
a decoder to generate weight selection signals for generating the first and second weight signals.
8. (Original) The circuit of claim 6, wherein  
the first and second weights have a substantially constant sum total weight.
9. (Original) The circuit of claim 8, wherein  
the Phase Digital to Analog converter includes  
a first current source drawing a first current that represents the first weight,  
a second current source drawing a second current that represents the sum total weight, and  
a third current source drawing a difference current between the second current and the first current, wherein the difference current is used to derive the second weight signal.
10. (Original) The circuit of claim 8, wherein  
the sum total weight equals a multiplication integer times four, and  
the first weight equals the multiplication integer times one of zero, one, two, three and four.
11. (Previously Presented) A device comprising:  
means for deriving a plurality of phased signals from a synchronizing signal associated with a color signal;  
means for deriving an adjustable delay signal from two of the phased signals that are apart from each other by an odd multiple of approximately 45 degrees; and

means for choosing an adjustment to the adjustable delay signal to improve conversion of the color signal into digital form., wherein at least one simulated phase signal is provided.

12. (Original) The device of claim 11, wherein the means for deriving the phased signals includes phase locked loop (PLL) circuit.
13. (Previously Presented) A method for generating delay signal for processing an analog color signal, comprising:
  - deriving a plurality of phased signals from a synchronizing signal associated with the analog color signal;
  - deriving the delay signal from two of the plurality of phased signals that are apart from each other by an odd multiple of approximately 45 degrees, wherein a delay generated by the delay signal is adjustable; and
  - choosing an adjustment to the delay signal to improve conversion of the analog color signal into digital form, wherein at least one simulated phase signal is provided.
14. (Original) The method of claim 13, wherein the phased signals are derived in a phase locked loop (PLL) circuit.
15. (Previously Presented) The method of claim 14, wherein the synchronizing signal is intended to generate a pixel clock in a display, and the phased signals replicate those of the pixel clock.
16. (Original) The method of claim 13, wherein deriving is performed by:
  - determining the location of a general requested delay in a phase diagram; and
  - selecting the two phased signals such that they define a sector between on the phase diagram that encompasses the general required delay.

17. (Original) The method of claim 16, further comprising:  
multiplying a first one of the selected phased signals with a first preselected weight,  
multiplying a second one of the selected phased signals with a second preselected weight, and  
adding together the first and the second multiplied phased signals.
18. (Original) The method of claim 17, further comprising:  
selecting first and second weights so as to simulate the general requested delay within the sector.
19. (Original) The method of claim 18, further comprising:  
subtracting the first weight from a preset sum total weight to derive the second weight.
20. (Original) The method of claim 19, wherein  
the sum total weight equals a multiplication integer times four, and  
the first weight equals the multiplication integer times one of zero, one, two,  
three and four.
21. (New) The circuit of claim 5, wherein the phase mixer includes:  
at least three differential pairs, wherein a first one of the differential pairs is  
arranged to multiply the first selected phased signal with the first weight and a second  
one of the differential pairs is arranged to multiply the second selected phased signal  
with the second weight, and wherein the phase mixer is configured to activate two  
differential pairs from the at least three differential pairs to derive the adjustable delay  
signal based, in part, on the at least one selected phase information signal
22. (New) The circuit of claim 21, wherein the more than two differential pairs  
includes at least four differential pairs.
23. (New) The circuit of claim 22, wherein the phase mixer is arranged such that the  
selection of active differential pairs sets the polarity of the adjustable delay signal.
24. (New) The circuit of claim 5, wherein the phase mixer includes:  
a first switch coupled between a first node and a second node, wherein the first switch is

